



TAUNT ELECTRIC CO.



7 kw
Home Generator
Systems



Running Watts (LP)*	7000
Running Watts (NG)*	6000
Surge Watts (LP)	10500
Surge Watts (NG)	9000
Engine Brand	Briggs & Stratton
Number of Cylinders	2
Voltage (V)	120/240
Running Amps	29.1(LP) 25(NG)
Surge Amps (LP)	43.75
Surge Amps (NG)	37.50
Alternator Type	Brush
Fuel Consumption (Cubic feet Per hour @ ½ load)	0.92 gal/hr (LP) 80 cubic ft/hr (NG)**
Fuel Consumption (Cubic feet Per hour @ full load)	1.56 gal/hr (LP) 137 cubic ft/hr (NG)**
Battery Charger	Yes
Hour Meter	Yes
Length (in)	31.5
Width (in)	30.25
Height (in)	34
Weight (lbs)	280
Warranty (Product)	2 Year
BTU's/Hour @ ½ load	80,000 (NG)
BTU's/Hour @ full load	137,000 (NG)

*NG = Natural Gas; LP = Liquid Propane.

**Fuel consumption rates are estimated bases on normal operating conditions at ½ load. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances, fuel flow rates may vary depending on these factors.