



TAUNT ELECTRIC CO.



12 kw
Home Generator
Systems



Running Watts (LP)*	12000
Running Watts (NG)*	11000
Engine Brand	Briggs & Stratton
Engine Series	Professional Series
Voltage (V)	120/240
CC	803
Operation	Fully Automatic
Alternator Type	Brushless, Computer friendly
Fuel Consumption (Cubic feet per hour @ ½ load)	Liquid Propane 51 Natural Gas 119**
Fuel Consumption (Cubic feet per hour @ full load)	2.19 gal/hr (LP) 195 cubic ft/hr (NG)
Weekly Exerciser	Yes
Battery Charger	Yes
Overcrank Protection	Yes
Hour Meter	Yes
Diagnostic Alerts with Remote System Status	Low oil shutdown, engine does not start, low frequency, engine overspeed, low voltage, low battery voltage, oil temp high, transfer switch fault
Length (in)	34.6
Width (in)	39.4
Height (in)	38.5
Weight (lbs)	520
Warranty (Product)	3 Year Limited Part & Labor
BTU's/Hour @ ½ load	102,000 (NG)
BTU's/Hour @ full load	195,000 (NG)

*NG = Natural Gas; LP = Liquid Propane.

**Fuel consumption rates are estimated bases on normal operating conditions at ½ load. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances, fuel flow rates may vary depending on these factors.