



## TAUNT ELECTRIC CO.



15 kw  
Home Generator  
Systems



Running Watts (LP)*	15000
Running Watts (NG)*	14000
Surge Watts (LP)	18500
Surge Watts (NG)	17000
Engine Brand	Briggs & Stratton
Engine Series	Vanguard
Voltage (V)	120/240
CC	895
Operation	Fully Automatic
Number of Cylinders	2
Alternator Type	Brush
Fuel Consumption (Cubic feet per hour @ ½ load)	Liquid Propane 1.56 gal/hr Natural Gas 126 cubic ft/hr**
Fuel Consumption (Cubic feet per hour @ full load)	2.99 gal/hr (LP) 242 cubic ft/hr (NG)
Weekly Exerciser	Yes
Battery Charger	Yes
Overcrank Protection	Yes
Hour Meter	Yes
Sound Attenuation	Sound Shield Technology
Diagnostic Alerts with Remote System Status	Low oil shutdown, fail to start, low frequency, engine overspeed, low voltage, low battery voltage, oil temp high, transfer switch fault
Length (in)	48.7
Width (in)	33.75
Height (in)	31.6
Weight (lbs)	562
Warranty (Product)	4 Year Limited
BTU's/Hour @ ½ load	126,000 (NG)
BTU's/Hour @ full load	242,000 (NG)

\*NG = Natural Gas; LP = Liquid Propane.

\*\*Fuel consumption rates are estimated bases on normal operating conditions at ½ load. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances, fuel flow rates may vary depending on these factors.